


NOTICE WIRE MODULE: PENDANT (ref LAA210-US)

**Read carefully before use and keep
IMPORTANT**

- . Only Lairial components must be used
- . Before use: Smooth the cable gently between the fingers to remove any folds & if the end of the lamp jewel (spring) is pushed in, gently stretch it to reshape it.
- . If the cable is damaged, it must be replaced exclusively by Lairial
- . The ceiling, around the electrical inlet, must be planar and not have points of weakness
- . Use a hook adapted to the nature of your ceiling (plaster, concrete, wood ...) - NOT supplied
- . Installation must be performed by a qualified electrician

Materials needed: wire stripper - flathead screwdriver 2.5 mm

Pavilion : Screw to maintain the wire



To connect the pendant to the ceiling

MOUNTING INSTRUCTIONS

- 1-Turn off the power on the electrical panel
- 2-Install the hook on the ceiling, next to the exit of the cables from the ceiling. CAUTION Do not injure electric cables in the ceiling
- 3- Fold the earth cable (green).



- 4- Pass the duct around the other 2 ceiling cables. WARNING, position the smooth end of the duct on the ceiling side
- 5- Strip the ceiling cables 5 mm.
- 6- Insert them into the case, white / grey cable in front of the blue (neutral) cable, black cable in front of the brown cable (phase). Screw in with the flat screwdriver. Pull the cables lightly to check for.



- 7- Return the housing to the block, inserting it between the 2 inner rails ↑
- 8- Bring the sheath back towards the housing, wedge it in the block by inserting the striated part into the cutout of the casing



- 9-Pass the luminaire cables through the baffle
- 10- Close the case. Insert the cables and the sheath into the ceiling



- 11- Hang the plastic piece to the hook.

- 12- Position the pavilion on the ceiling by sliding it gently along the cable. Check that the cable remains suspended from the hook.

- 13 -While holding the pavilion to the ceiling with the hand, turn the screw on the side to fix it on the cable
- 14- Connect the lighting module

CONNECTING /DISCONNECTING

CAUTION: Before connecting, switch off

A-CONNECT



- 1- Prepare the modules (lighting and wire)



- 2- Insert the male connector into the female connector until you hear a "click".



- 3- Move the two springs together



- 4- Insert the wire module holder into the spring of BulM (Blistering at the tip)



- 5- Hold the BulM spring with your hand and turn the other part of the spring clockwise. Pull lightly to check for

B-DISCONNECT

- 1- Hold the BulM spring with your hand and unscrew the spring from the connector module counterclockwise. IMPORTANT: do not disengage the springs by pulling
- 2- Disconnect by pulling lightly

IMPORTANT: the spring has only aesthetic function. Do not pull on the turns, it will distort it and harm the aesthetics of the object

CLEANING

- 1- Switch off. If necessary, disconnect the modules.
- 2- Aspirate the dust with the small brush of the vacuum cleaner